

Exercise session 6

H_∞ Optimization of Coprime Factors. H_∞ Loop Shaping. v-Gap Metric

Reading Assignment

Read [Zhou] Ch. 16

Exercises

E7.1 [Zhou] 16.5

E7.2 [Zhou] 16.8

E7.3 Consider a simplified model of a satellite with two highly flexible solar arrays (Salehi, 10th IFAC Symposium, 1985)

$$\begin{aligned} \dot{x} &= \begin{pmatrix} 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & -\omega^2 & -2\zeta\omega \end{pmatrix} x + \begin{pmatrix} 0 \\ 1.7319e-05 \\ 0 \\ 3.7859e-04 \end{pmatrix} u + \begin{pmatrix} 0 \\ 1.7319e-05 \\ 0 \\ 3.7859e-04 \end{pmatrix} v, \\ y &= (1 \ 0 \ 1 \ 0) x. \end{aligned}$$

where $\omega = 1.539 \text{ rad/sec}$ is the frequency of the flexure mode and $\zeta = 0.003$ is the flexural damping ratio. Here u is the control torque (Nm), v is a constant disturbance torque (Nm) and y is the roll angle measurement (rad).

Required performance specification: y must stay within $0.04^\circ \approx 0.0007 \text{ rad}$ pointing accuracy due to $0.3 Nm$ step torque disturbances.

- Using [Zhou,16.12] prove the following bound

$$|(I - PK)^{-1}P| \leq \frac{\gamma}{|W|}$$

where $W = W_1 W_2$ is a single shaping function (for SISO plants).

- Show that the performance specification is met for the constant shape function $W = 2000$.
- Find the controller by H_∞ loop shaping procedure. Draw the Bode plots of the nominal P , shaped P_s and achieved WPK_∞ open loops. Compare.
- Due to small steady-state error ($\approx 0.018^\circ$) introduce another shaping function

$$W = \frac{10000(s + 0.4)}{s}.$$

Show that the performance specification is met and the full steady-state disturbance rejection is guaranteed.

5. Repeat Item (c) for the new W .

Hand-In problem:

H7.1 Let a nominal plant be given by $P = \frac{s-1}{s(s+2)}$ and we select $W = k$, a constant, as the shaping function. Thus $P_s = \frac{k(s-1)}{s(s+2)}$.

1. Calculate $b_{opt}(P_s)$ and for 4 different choices of $W = k$

$$k = [.1 \ 1 \ 5 \ 10].$$

What k 's give better loop shape for controller design?

2. For all 4 choices of W : Find the optimal controller K_∞ . Plot the Bode diagram of the specified loop shape P_s and the achieved loop shape $WK_\infty P$.